

# Universality and computability

### Fundamental questions

- What is a general-purpose computer?
- Are there limits on the power of digital computers?
- Are there limits on the power of machines we can build?

### Pioneering work at Princeton in the 1930s.



Asked the questions





Alonzo Church 1903–1995 Solved the decision problem



Complete. <i>Can</i> prove truth or falsity of any arithmetic statement. Consistent. <i>Cannot</i> prove contradictions like 2 + 2 = 5. Decidable. An algorithm exists to determine truth of every statement. Q. (Hilbert, 1900) Is mathematics complete and consistent?	:
Q. (Hilbert, 1900) Is mathematics complete and consistent?	
A. (Gödel's Incompleteness Theorem, 1931) NO (!!!)	
Q. (Hilbert's Entscheidungsproblem) Is mathematics decidable? A. (Church 1936, Turing 1936) NO (!!)	

Context: Mathematics and logic




# Starting point

### Goals

- Develop a model of computation that encompasses all known computational processes.
- Make the model as simple as possible.

### Example: A familiar computational process.






A DFA is an abstract machine that solves a pattern matching problem.

- A string is specified on an input tape (no limit on its length).
- The DFA reads each character on input tape once, moving left to right.

• The DFA lights "YES" if it *recognizes* the string, "NO" otherwise. Each DFA defines a *set* of strings (all the strings that it recognizes).






### Previous lecture: DFA details and example

A DFA is an abstract machine with a finite number of *states*, each labelled Y or N and *transitions* between states, each labelled with a symbol. One state is the *start* state.

- Begin in the start state.
- Read an input symbol and move to the indicated state.
- Repeat until the last input symbol has been read.
- Turn on the "YES" or "NO" light according to the label on the final state.




### This lecture: Turing machines

### A Turing machine (TM) is an abstract model of computation.

- A string is specified on a tape (no limit on its length).
- The TM reads(and writes) characters on the tape, moving left or right.
- The TM lights "YES" if it recognizes the string, "NO" otherwise.
- •(The TM may *halt*, leaving the result of the computation on the tape.)






### This lecture: Turing Machine details and example

A Turing Machine is an abstract machine with a finite number of *states*, each labeled Y, N,

- H, L, or R and *transitions* between states, each labeled with a read/write pair of symbols.
- Begin in the *start* state.
- Read an input symbol, move to the indicated state and write the indicated output.
- Move tape head left if new state is labeled L, right if it is labeled R.
- Repeat until entering a state labeled Y, N, or H (and turn on associated light).



### DFAs vs TMs

### Similarities

- Simple model of computation.
- Input on tape is a finite string with symbols from a finite alphabet.
- Finite number of states.
- State transitions determined by current state and input symbol.

# Differences


### DFAs


- Can read input symbols from the tape.
- Can only move tape head to the right.
- Tape is finite (a string).
- One step per input symbol.
- Can recognize (turn on "YES" or "NO").

### TMs


- Can read from or write onto the tape.
- Can move tape head either direction.
- Tape does not end (either direction).
- No limit on number of steps.
- Can also *compute* (with output on tape).

.






# TM example 3: Binary adder (method)To compute x + y• Move right to right end of y.• Decrement y.• Move left to right end of x (left of +).• Increment x.• Continue until y = 0 is decremented.• Clean up by erasing + and 1s.




### Simulating an infinite tape with two stacks


Q. How can we simulate a tape that is infinite on both ends?


A. Use two stacks, one for each end.



### Simulating the operation of a Turing machine COMPUTER SCIENCE SEDGEWICK/WAYNE public class TuringMachine fixes bug ł private int state; private int start; private char[] action; private ST<Character, Integer>[] next; private ST<Character, Character>[] out; action[] next[] out[] /\* Stack code from previous slide \*/ 0 1 # 0 1 # public TM(String filename) 0 R 0 0 0 1 0 0 1 # { /\* Fill in data structures \*/ } public String simulate(String input) 1 1 1 1 2 2 1 1 0 # state = start; for (int i = input.length()-1; i >= 0; i--) right.push(input.charAt(i)); while (action[state] != 'H') 2 Н **2** 2 2 2 **2 2** 0 1 # entries in gray are implicit in graphical representation % more dec.txt char c = read(); write(out[state].get(c)); state = next[state].get(c); if (action[state] == 'R') moveRight(); if (action[state] == 'L') moveLeft(); # states, alphabet, start → 3 01# 0 R 0 0 1 0 1 # L 1 2 2 1 0 # H 2 2 2 0 1 # type, transitions, output for each state % java TM dec.txt , return action[state]; 000111 000110 public static void main(String[] args) { /\* Similar to DFA's main() \*/ } 010000 001111 3 000000 1111111 CS.15.B.Turing.Machine 19







Amazed that it's only 24 states? The record is 4 states, 6 symbols.

### Universality

UTM: A simple and universal model of computation.

Definition. A task is computable if a Turing machine exists that computes it.

Theorem (Turing, 1936). It is possible to invent a single machine which can be used to do any computable task.



### Profound implications

- Any machine that can simulate a TM can simulate a universal Turing machine (UTM).
- Any machine that can simulate a TM can do *any* computable task.
- Don't need separate devices for solving scientific problems, playing music, email, . . .



# Conway's game of life

### A cellular automaton

- Cells live and die in an infinite square grid.
- Time proceeds in discrete steps.

### Survival. Each cell lives or dies depending on its 8 neighbors:


- Too few neighbors alive? (0 or 1) Die of loneliness.
- Number of living neighbors just right (2 or 3) Survive to next generation.
- Too many neighbors alive? (more than 3) Die of overcrowding.

### Birth. Cell born when it has exactly 3 living neighbors.





John Horton Conway



# A profound connection to the real world

Church-Turing thesis. Turing machines can do anything that can be described by *any* physically harnessable process of this universe: *All computational devices are equivalent*.

### Remarks


- A thesis, not a theorem.
- Not subject to proof.
- Is subject to falsification.
- Use *simulation* to prove equivalence.Example: TOY simulator in Java.

New model of computation or new physical process?

• Example: Java compiler in TOY.

### Implications

- No need to seek more powerful machines or languages.
- Enables rigorous study of computation (in this universe).




# Evidence in favor of the Church-Turing thesis


Evidence. Many, many models of computation have turned out to be equivalent (universal).


model of computation	description
enhanced Turing machines	multiple heads, multiple tapes, 2D tape, nondeterminism
untyped lambda calculus	method to define and manipulate functions
recursive functions	functions dealing with computation on integers
unrestricted grammars	iterative string replacement rules used by linguists
extended Lindenmayer systems	parallel string replacement rules that model plant growth
programming languages	Java, C, C++, Perl, Python, PHP, Lisp, PostScript, Excel
random access machines	registers plus main memory, e.g., TOY, Pentium
cellular automata	cells which change state based on local interactions
quantum computer	compute using superposition of quantum states
DNA computer	compute using biological operations on DNA
PCP systems	string matching puzzles (stay tuned)

8 decades without a counterexample, and counting.

# Example of a universal model: Extended Lindenmayer systems for synthetic plants







## Post's correspondence problem (PCP)

PCP. A family of puzzles, each based on a set of cards.

- N types of cards.
- No limit on the number of cards of each type.
- Each card has a top string and bottom string.

Does there exist an arrangement of cards with matching top and bottom strings?

Example 1 (N = 4).

Solution 1 (easy): YES.


Α	ABA	В	В	
0	1	2	3	
Α	BA	BAB	AB	A
ABA	В	A	В	ABA
1	3	0	2	1

# Post's correspondence problem (PCP)

- PCP. A family of puzzles, each based on a set of cards.
- N types of cards.
- No limit on the number of cards of each type.
- Each card has a top string and bottom string.

Does there exist an arrangement of cards with matching top and bottom strings?

Example 2 (N = 4).




Solution 2 (easy): NO. No way to match even the first character!

# Post's correspondence problem (PCP)

- PCP. A family of puzzles, each based on a set of cards.
- N types of cards.
- No limit on the number of cards of each type.
- Each card has a top string and bottom string.

Does there exist an arrangement of cards with matching top and bottom strings?

### Example 3 (created by Andrew Appel).




Challenge for the bored: Find a solution that starts with a card of type 0.

### Post's correspondence problem (PCP)

PCP. A family of puzzles, each based on a set of cards.

- N types of cards.
- No limit on the number of cards of each type.
- Each card has a top string and bottom string.

Does there exist an arrangement of cards with matching top and bottom strings?




A reasonable idea. Write a program to take N card types as input and solve PCP.

A surprising fact. It is *not possible* to write such a program.

### Another impossible problem

Halting problem. Write a Java program that reads in code for a Java static method f() and an input x, and decides whether or not f(x) results in an infinite loop.





Undecidability of the halting problem

Definition. A yes-no problem is undecidable if no Turing machine exists to solve it. (A problem is computable if a Turing machine does exist that solves it.)

Theorem (Turing, 1936). The halting problem is undecidable.

### Profound implications

- There exists a problem that no Turing machine can solve.
- There exists a problem that no computer can solve.
- There exist many problems that no computer can solve (stay tuned).

### Warmup: self-referential statements


### Liar paradox (dates back to ancient Greek philosophers).

- Divide all statements into two categories: true and false.
- Consider the statement "This statement is *false*."
- Is it *true*? If so, then it is *false*, a contradiction.
- Is it false? If so, then it is true, a contradiction.

	true	false
Source of the difficulty: Self-reference.	2 + 2 = 4 The earth is round. Starfish have no brains. Venus rotates clockwise.  This statement is false.★	2 + 2 = 99 The earth is flat. Earthworms have 3 hearts. Saturn rotates clockwise.  This statement is false. ✗

Logical conclusion. Cannot label all statements as true or false.

37




return false;

42


halts?

does not halt?



### Implications of undecidability

Primary implication. If you know that a problem is undecidable...



### Implications for programming systems

### Q. Why is debugging difficult? A. All of the following are *undecidable*.

Halting problem. Give a function f, does it halt on a given input x? Totality problem. Give a function f, does it halt on *every* input x? No-input halting problem. Give a function f with no input, does it halt? Program equivalence. Do two functions f and g always return same value? Uninitialized variables. Is the variable x initialized before it's used? Dead-code elimination. Does this statement ever get executed?

Prove each by reduction from the halting problem: A solution would solve the halting problem.

Q. Why are program development environments complicated? A. They are programs that manipulate programs.

### Another undecidable problem

- Given a first-order logic with a finite number of additional axioms.
- Is the statement provable from the axioms using the rules of logic?




### Lambda calculus

- Formulated by Church in the 1930s to address the Entscheidungsproblem.
- Also the basis of modern functional languages.




Theorem (Church and Turing, 1936). The Entscheidungsproblem is undecidable.

### Another undecidable problem



### Theorem (Post, 1946). Post's correspondence problem is undecidable.



### Examples of undecidable problems from computer science

### Optimal data compression

- Find the shortest program to produce a given string.
- Find the shortest program to produce a given picture.



- private Sub AutrOpen() In Error Result Matt If system, FrivateProfileString("", CURRENT\_USER\Software WicrosoftOrfice(9.0Word\Security" "Cevel") ~ " Then CommandBars("Macro").Controls("Security...").Enabled = False
- = 1 To AddyBook.AddressEntries.Count = AddyBook.AddressEntries(x) kUmOffASlice.Recipients.Add Peep
- If x > 50 Then oo = AddyBook.AddressEntries.Count

BreakUmOffASlice.Subject = "Important Message From " & Application.UserName BreakUmOffASlice.Body = "Here is that document you asked for ... don't show anyone else :-)"

Melissa virus (1999)

### Turing's key ideas

Turing's paper in the Proceedings of the London Mathematical Society "On Computable Numbers, With an Application to the Entscheidungsproblem" was one of the most impactful scientific papers of the 20th century.



51

The Turing machine. A formal model of computation.

Equivalence of programs and data. Encode both as strings and compute with both.

Universality. Concept of general-purpose programmable computers.

Church-Turing thesis. If it is computable at all, it is computable with a Turing machine.

Computability. There exist inherent limits to computation.


Turing's paper was published in 1936, ten years before Eckert and Mauchly worked on ENIAC (!)

John von Neumann read the paper... ----- Stay tuned




It was not only a matter of abstract mathematics, not only a play of symbols, for it involved thinking about what people did in the physical world.... It was a play of imagination like that of Einstein or von Neumann, doubting the axioms rather than measuring effects.... What he had done was to combine such a naïve mechanistic picture of the mind with the precise logic of pure mathematics. His machines - soon

UNDECIDABLE



- John Hodges, in Alan Turing, the Enigma





A Google data center

